Table 3-3.9.1
Hazard Risk Category Classification

NFPA 70E Standard for Electrical Safety Requirements for Employee Workplaces

Table 3-3.9.1 Hazard Risk Category Classification

Task (Assumes Equipment Is Energized, and Work Is Done Within The Flash Protection Boundary)	Hazard / Risk Category	V-Rated Gloves	V-Rated Tools
Panelboards rated 240 V and below – Notes 1 and 3	-	-	-
Circuit breaker (CB) or fused switch operation with covers on	0	N	N
CB or fused switch operation with covers off	0	N	N
Work on energized parts, including voltage testing	1	Y	Y
Remove/install CBs or fused switches	1	Y	Y
Removal of bolted covers (to expose bare, energized parts)	1	N	N
Opening hinged covers (to expose bare, energized parts)	0	N	N

Notes:

1. 25 kA short circuit current available, 0.03 second (2 cycle) fault clearing time.

3. For <10 kA short circuit available, the Hazard / Risk Category required may be reduced by one Number.

NFPA 70E Standard for Electrical Safety Requirements for Employee Workplaces

Table 3-3.9.1 Hazard Risk Category Classification (Continued)

Task (Assumes Equipment Is Energized, and Work Is Done Within The Flash Protection Boundary)	Hazard / Risk Category	V-Rated Gloves	V-Rated Tools
600 V Class Motor Control Centers (MCCs) – Notes 2 (except as indicated) and 3	_	_	_
Work on control circuits with energized parts >120V exposed	2*	Y	Y
Insertion or removal of individual starter ñbucketsò from MCC ð Note 4	3	Y	N
Application of safety grounds, after voltage test	2*	Y	N
Removal of bolted covers (to expose bare, energized parts)	2*	N	N
Opening hinged covers (to expose bare, energized parts)	1	N	N

Notes:

2. 65 kA short circuit current available, 0.03 second (2 cycle) fault clearing time.

2* Means that a double-layer switching hood and hearing protection are required for this task in addition to the other Hazard / Risk Category 2 requirements of Table 3-3.9.2 of Part II

3. For <10 kA short circuit available, the Hazard / Risk Category required may be reduced by one Number.

4. 65 kA short circuit current available, 0.33 second (20 cycle) fault clearing time.

NFPA 70E Standard for Electrical Safety Requirements for Employee Workplaces

Table 3-3.9.1 Hazard Risk Category Classification (Continued)

Task (Assumes Equipment Is Energized, and Work Is Done Within The Flash Protection Boundary)	Hazard / Risk Category	V-Rated Gloves	V-Rated Tools
600 V Class Switchgear (with power circuit breakers or fused switches) — Notes 5 and 6	–	–	–
Work on control circuits with energized parts >120 V exposed	2*	Y	Y
Insertion or removal (racking) of CBs from cubicles, doors open	3	N	N
Insertion or removal (racking) of CBs from cubicles, doors closed	2	N	N
Application of safety grounds, after voltage test	2*	Y	N
Removal of bolted covers (to expose bare, energized parts)	3	N	N
Opening hinged covers (to expose bare, energized parts)	2	N	N

NFPA 70E Standard for Electrical Safety Requirements for Employee Workplaces

Table 3-3.9.1 Hazard Risk Category Classification (Continued)

Task (Assumes Equipment Is Energized, and Work Is Done Within The Flash Protection Boundary)	Hazard / Risk Category	V-Rated Gloves	V-Rated Tools
NEMA E2 (fused contactor) Motor Starters, 2.3 kV through 7.2 kV	_	_	_
Insertion or removal (racking) of starters from cubicles, doors closed	2	N	N
Application of safety grounds, after voltage test	3	Y	N
Removal of bolted covers (to expose bare, energized parts)	4	N	N
Opening hinged covers (to expose bare, energized parts)	3	N	N

NFPA 70E Standard for Electrical Safety Requirements for Employee Workplaces

Table 3-3.9.1 Hazard Risk Category Classification (Continued)

Task (Assumes Equipment Is Energized, and Work Is Done Within The Flash Protection Boundary)	Hazard / Risk Category	V-Rated Gloves	V-Rated Tools
Metal Clad Switchgear, 1 kV and above	_	_	_
CB or fused switch operation with enclosure doors closed	2	N	N
Reading a panel meter while operating a meter switch	0	N	N
CB or fused switch operation with enclosure doors open	4	N	N
Work on energized parts, including voltage testing	4	Y	Y
Work on control circuits with energized parts 120 V or below, exposed	2	Y	Y
Work on control circuits with energized parts >120 V, exposed	4	Y	Y
Insertion or removal (racking) of CBs from cubicles, doors open	4	N	N

Table 3-3.9.1 Hazard Risk Category Classification (Continued)

NFPA 70E Standard for Electrical Safety Requirements for Employee Workplaces

Table 3-3.9.1 Hazard Risk Category Classification (Continued)

Task (Assumes Equipment Is Energized, and Work Is Done Within The Flash Protection Boundary)	Hazard / Risk Category	V-Rated Gloves	V-Rated Tools
Other Equipment 1 kV and above	_	_	_
Insulated cable examination, in manhole or other confined space	4	Y	N
Insulated cable examination, in open area	2	Y	N

Table 3-3.9.1 Hazard Risk Category Classification (Continued)

Legend:

V-rated Gloves are gloves rated and tested for the maximum line-to-line voltage upon which work will be done.

V-rated Tools are tools rated and tested for the maximum line-to-line voltage upon which work will be done.

2* means that a double-layer switching hood and hearing protection are required for this task in addition to
the other Hazard/Risk Category 2 requirements of Table 3-3.9.2 of Part II.

Y = yes (required)

N = no (not required)

Notes:

1. 25 kA short circuit current available, 0.03 second (2 cycle) fault clearing time.
2. 65 kA short circuit current available, 0.03 second (2 cycle) fault clearing time.
3. For < 10 kA short circuit current available, the Hazard/Risk Category required may be reduced by one
Number.
4. 65 kA short circuit current available, 0.33 second (20 cycle) fault clearing time.
5. 65 kA short circuit current available, up to 1.0 second (60 cycle) fault clearing time.
6. For < 25 kA short circuit current available, the Hazard/Risk Category required may be reduced by one
Number.

Table 3-3.9.2
Protective Clothing and Personal Protective Equipment (PPE) Matrix

NFPA 70E Standard for Electrical Safety Requirements for Employee Workplaces

Table 3-3.9.2 Protective Clothing and Personal Protective Equipment (PPE) Matrix

NFPA 70E Standard for Electrical Safety Requirements for Employee Workplaces

Table 3-3.9.2 Protective Clothing and Personal Protective Equipment (PPE) Matrix

Legend:
AN = As needed
AL = Select one in group
AR = As required
X = Minimum required

Notes:
1. See Table 3-3.9.3. (ATPV is the Arc Thermal Performance Exposure Value for a garment in cal/cm^2 .)
2. If voltage-rated gloves are required, the leather protectors worn external to the rubber gloves satisfy this requirement.
3. Class 1 is only defined if determined by Notes 3 or 6 of Table 3-3.9.1 of Part II.
4. Regular weight (minimum 12 oz/yd^2 fabric weight), untreated, denim cotton blue jeans are acceptable in lieu of FR pants. The FR pants used for Hazard/Risk Category 1 shall have a minimum ATPV of 5.
5. Alternate is to use FR coveralls (minimum ATPV of 5) instead of FR shirt and FR pants.
6. If the FR pants have a minimum ATPV of 8, long pants of untreated natural fiber are not required beneath the FR pants.
7. Alternate is to use FR coveralls (minimum ATPV of 5) over untreated natural fiber pants and T-shirt.
8. A double-layer switching hood and hearing protection are required for the tasks designated 2* in Table 3-3.9.1 of Part II.
9. Alternate is to use two sets of FR coveralls (each with a minimum ATPV of 5) over untreated natural fiber clothing, instead of FR coveralls over FR shirt and FR pants over untreated natural fiber clothing.

Table 3-3.9.3
Protective Clothing Characteristics

NFPA 70E Standard for Electrical Safety Requirements for Employee Workplaces

Table 3-3.9.3 Protective Clothing Characteristics

Typical Protective Clothing Systems			
Hazard / Risk Category	**Clothing Description (Number of clothing layers is given in parentheses)**	**Total Weight oz/yd^2**	**Minimum Arc Thermal Performance Exposure Value (ATPV)* or Break-open Threshold Energy (E_{BT})* Rating of PPE cal/cm^2**
0	Untreated cotton (1)	4.5 ï 7	N/A
1	FR shirt and FR pants (1)	4.5 ï 8	5
2	Cotton underwear plus FR shirt and FR pants (2)	9 ï 12	8
3	Cotton underwear plus FR shirt and FR pants plus FR coverall (3)	16 ï 20	25
4	Cotton underwear plus FR shirt and FR pants plus double layer switching coat and pants (4)	24 ï 30	40

***ATPV is defined in the ASTM P S58 standard arc test method for flame resistant (FR) fabrics as the incident energy that would just cause the onset of a second degree burn (1.2 cal/cm^2**

Figure A-1-2.4
Limits of Approach

NFPA 70E Standard for Electrical Safety Requirements for Employee Workplaces

Table 2-1.3.4 Approach Boundaries to Live Parts for Shock Protection.
(All dimensions are distance from live part to employee.)

(1)	(2)	(3)	(4)	(5)
	Limited Approach Boundary[1]		Restricted Approach Boundary[1]	
Nominal System Voltage Range, Phase to Phase	Exposed Movable Conductor	Exposed Fixed Circuit Part		

P /MCID 160).7 264.22 Tm(M1 0vTmeTBen(ch)]T60(Adde 0 1 261.94 264.22 Tm5456.66 ET EMC /P /MCID 15>> BDC

NFPA 70E Standard for Electrical Safety Requirements for Employee Workplaces

Figure A-1-2.4 Limits of Approach